

Filename: PMP8803_RevA_bom.xls

Date: 01/22/2013

PMP8803 REV A BOM

COUNT	REFDES	VALUE	DESCRIPTION	SIZE	PART NUMBER	MFR
1	C18	100pF	Capacitor, Ceramic, 16V, X7R, 10%	603	STD	Std
1	C19	0.01uF	Capacitor, Ceramic, 16V, X7R, 10%	603	STD	Std
1	C21	0.033uF	Capacitor, Ceramic, 16V, X7R, 10%	603	STD	Std
1	C20	0.1uF	Capacitor, Ceramic, 16V, X7R, 10%	603	STD	Std
4	C1-4	0.1uF	Capacitor, Ceramic, 100V, X7R, 10%	603	STD	Std
2	C22 C28	1uF	Capacitor, Ceramic, 25V, X5R, 20%	603	STD	Std
1	C7	680pF	Capacitor, Ceramic, 50V, C0G, 10%	805	STD	Std
4	C17 C24-26	1000pF	Capacitor, Ceramic, 100V, X7R, 10%	805	STD	Std
2	C11 C23	0.1uF	Capacitor, Ceramic, 100V, X7R, 10%	805	STD	Std
1	C15	0.22uF	Capacitor, Ceramic, 25V, X7R, 10%	805	STD	Std
2	C9-10	2.2uF	Capacitor, Ceramic, 100V, X7R, 10%	1210	STD	Std
3	C12-14	22uF	Capacitor, Ceramic, 16V, X5R, 20%	1210	C3225X5R1C226M	TDK
1	C5	1000pF	Capacitor, Ceramic Chip, 2KV, 10%	1808	STD	Std
2	C6 C27	2200pF	Capacitor, Ceramic, 2KV, X7R, 20%	1812	STD	Std
1	C16	10uF	Capacitor, Aluminum, 25V, 20%	4x5.8mm	EEEFK1E100R	Panasonic
1	C8	22uF	Capacitor, Aluminum Electrolytic, 100V, 20%	8x10.2mm	EEEFK2A220P	Panasonic
1	D1		Diode, Transient Voltage Suppressor, 400W, 58V	SMA	SMAJ58A	Diodes, Inc
1	D10		Diode, Switching, 200mA, 75V, 225mW	SOT-23	BAS16	On Semi
1	D12		Diode, Dual Schottky, 200mA, 30V	SOT23	BAT54S	Diodes, Inc
2	D2-3		Bridge Rectifier, 100V, 0.8A, Glass Passivated, SMD	MINI DIP4	HD01	Diodes, Inc
1	D4		Diode, Schottky, 3A, 60V	SMC	B360	Diodes, Inc
2	D8 D14		Diode, Rectifier, 1A, 200V	SMA	MURA120	On Semi
4	FB1-4	220	Bead, Ferrite, SMT, 220 Ohms, 3A	805	MPZ2012S221A	TDK
2	J1-2		Connector, Jack, Modular, 8 POS	0.705 x 0.820 inch	520252	AMP
2	J3 J6		Terminal Block, 2-pin, 6-A, 3.5mm	0.27 x 0.25 inch	ED555/2DS	OST
1	L1	10uH	Inductor, SMT, 750mA, 350 milliohm	4x4mm	LPS4012-103ML	Coilcraft
1	Q2		MOSFET, N-ch, 150-V, 4.1A, 66 milliOhms	SO8	FDS2582	Fairchild
1	R14	0	Resistor, Chip, 1/16W, 1%	603	STD	Std
1	R13	10	Resistor, Chip, 1/16W, 1%	603	STD	Std
4	R1-4	75	Resistor, Chip, 1/16W, 1%	603	STD	Std
1	R12	90.9	Resistor, Chip, 1/16W, 1%	603	STD	Std
1	R20	1K	Resistor, Chip, 1/16W, 1%	603	STD	Std
1	R28	1.5K	Resistor, Chip, 1/16W, 1%	603	STD	Std
2	R22-23	2K	Resistor, Chip, 1/16W, 1%	603	STD	Std

1	R100	4.99K	Resistor, Chip, 1/16W, 1%	603	STD	Std
2	R16 R21	10K	Resistor, Chip, 1/16W, 1%	603	STD	Std
1	R24	11.5K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R7	24.9K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R27	39.2K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R19	44.2K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R10	59K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R11	80.6K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R26	392K	Resistor, Chip, 1/16W,1%	603	STD	Std
1	R9	10	Resistor, Chip, 1/10W, 5%	805	STD	Std
1	R6	39K	Resistor, Chip, 1/10W, 5%	805	STD	Std
1	R18	0.39	Resistor, Chip, 1/2W, 1%	2010	STD	Std
1	R5	20	Resistor, Chip, 1/2W, 5%	2010	STD	Std
1	T1		XFMR, 1000 Base-T, Ratio 1:1	0.500 x 0.370 inch	H2019	Pulse
1	T2		Transformer, Flyback For PoE, 12V, 1A	0.700 x 0.530 inch	POE13P-12L	Coilcraft
1	U2		IC, Photocoupler, 3750VRMS, 80-160% CTR	MF4	TCMT1107	Vishay
1	U3		IC, Shunt Regulator, 2.5V Ref, 36V, 100mA, 1%	SOT23-5	TL431ACDBVR	TI
1	U1		IC, IEEE 802.3af Integrated Primary Side Controller	TSSOP14	TPS23753APW	TI

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com