

Variant: 001
 Generated: 6/15/2020 1:49:45 PM
 TID #: TIDA050042



TIDA050042 REV A1 Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	IPC1	1		TIDA050042	Any	Printed Circuit Board	
2	C1, C3	2	0.1uF	06035C104KAT2A	AVX	CAP, CERM, 0.1 uF, 50 V, +/- 10%, X7R, 0603	0603
3	C2, C4	2	10uF	CGA6P3X7S1H106K250AB	TDK	CAP, CERM, 10 uF, 50 V, +/- 10%, X7S, AEC-Q200 Grade 1, 1210	1210
4	C5, C7	2	0.1uF	GRM155R71C104KA88D	MuRata	CAP, CERM, 0.1 uF, 16 V, +/- 10%, X7R, 0402	0402
5	D1, D2	2	40V	B340LA-13-F	Diodes Inc.	Diode, Schottky, 40 V, 3 A, SMA	SMA
6	D3	1	30V	BAT54HT1G	ON Semiconductor	Diode, Schottky, 30 V, 0.2 A, SOD-323	SOD-323
7	J1	1		TSW-105-07-G-S	Samtec	Header, 100mil, 5x1, Gold, TH	5x1 Header
8	J2, J3	2		HTSW-102-07-G-S	Samtec	Header, 100mil, 2x1, Gold, TH	Header, 100mil, 2x1, TH
9	L1	1	4.7uH	7440650047	Würth Elektronik	Inductor, Shielded Drum Core, Ferrite, 4.7 uH, 4.2 A, 0.02 ohm, SMD	WE-TPC-XLH2
10	R1, R14	2	10.0k	RT0603DRE0710KL	Yageo America	RES, 10.0 k, 0.5%, 0.1 W, 0603	0603
11	R2, R6, R8, R9	4	1.00k	RT0603DRE071KL	Yageo America	RES, 1.00 k, 0.5%, 0.1 W, 0603	0603
12	R3	1	49.9	ERJ-3EKF49R9V	Panasonic	RES, 49.9, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
13	R4, R5	2	0.1	CSR1206FKR100	Stackpole Electronics Inc	RES, 0.1, 1%, 0.5 W, 1206	1206
14	R7	1	9.10k	RG1608P-912-B-T5	Susumu Co Ltd	RES, 9.10 k, 0.1%, 0.1 W, 0603	0603
15	R10	1	340k	RC0603FR-07340KL	Yageo	RES, 340 k, 1%, 0.1 W, 0603	0603
16	R11	1	1.00Meg	MCT06030C1004FP500	Vishay/Beyschlag	RES, 1.00 M, 1%, 0.125 W, 0603	0603
17	R12	1	294k	CRCW0603294KFKEA	Vishay-Dale	RES, 294 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
18	R13	1	0	CRCW06030000Z0EA	Vishay-Dale	RES, 0, 5%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
19	TP1	1		5001	Keystone	Test Point, Miniature, Black, TH	Black Miniature Testpoint
20	U1	1		TVS3300DRVR	Texas Instruments	33-V Precision Surge Protection Clamp, DRV0006A (WSON-6)	DRV0006A
21	U2	1		TPS92200D1DDCR	Texas Instruments	4 V to 30-V Input Voltage, 1.5 A Output Current, Synchronous Buck LED Driver With Flexible Dimming Options, DDC0006A (SOT-23-THN-6)	DDC0006A
22	U3	1		TLV9002IDDFR	Texas Instruments	TLV9002IDDFR, DDF0008A (SOT-23-THN-8)	DDF0008A
23	U4	1		TLV7021DCKR	Texas Instruments	Small-Size Micropower Low-Voltage Comparator, DCK0005A (SOT-SC70-5)	DCK0005A
24	U5	1		TL431AIDBZR	Texas Instruments	Adjustable Precision Shunt Regulator, 34 ppm / degC, 100 mA, -40 to 85 degC, 3-pin SOT-23 (DBZ), Green (RoHS & no Sb/Br)	DBZ0003A
25	C6, C8	0	0.068uF	CGA3E2X7R1H683K080AA	TDK	CAP, CERM, 0.068 uF, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2020, Texas Instruments Incorporated