

Bill of Materials

TI DESIGNS

TIDM-FRAM-IRREFLECTIONSENSING

Item	Qty	Reference	Value	Part Description	Manufacturer	Manufacturer Part Number	Alternate Part	PCB Footprint	Note
1	4	C3,C9,C12,C15	0.1uF	CAP, CERM, 0.1uF, 16V, +/-5%, X7R, 0603	Kemet	C0603C104J4RACTU		0603	C9, C12 DNP
2	1	C8	100uF	CAP, CERM, 100 uF, 6.3 V, +/- 20%, X5R, 1210	MuRata	GRM32ER60J107ME20L		1210	
3	3	C6,C10,C11	1uF	CAP, CERM, 1 uF, 10 V, +/- 10%, X5R, 0603	MuRata	GRM185R61A105KE36D		0603	C10, C11 DNP
4	2	C7,C14	10uF	CAP, CERM, 10 uF, 10 V, +/- 10%, X5R, 1210	Kemet	C1210C106K8PACTU		1210	
5	2	C5,C13	1nF	CAP, CERM, 1000pF, 100V, +/-5%, X7R, 0603	AVX	06031C102JAT2A		0603	C13 DNP
6	1	C1	3.3pF	CAP, CERM, 3.3 pF, 50 V, +/- 8%, COG/NPO, 0603	AVX	06035A3R3CAT2A		0603	
7	2	C2,C4	10uF	COG/NPO, 0603	Kemet	C0603C106M9PACTU		0603	
8	1	S1		SWITCH TACTILE 6.0x6.0x4.3mm 100gf 1 N 50mA 12 V	ALPS	SKHHAJA010			EVQ-PAD04M
9	1	D3	Red	LED, Red, SMD	Rohm	SML-311UTT86			SML-31_Red
10	1	D4	30V	Diode, Schottky, 30V, 0.5A, SOD-123	ON Semiconductor	MBR0530T1G			SOD-123
11	1	D1	60V	Photodiode, 60V 215mW 875nm	Vishay Semiconductors	BPV10NF			T-1 3/4
12	1	D2		IR Emitter, 15 Degree 210mW 950nm	Vishay Semiconductors	TSUS5201			T-1 3/4
13	3	J1,J2,J3		Header, 100mil, 2x1, Tin, TH	Molex	90120-0122			CONN_90120-0122
14	1	L1	10uH	Inductor, Shielded, Ferrite, 10uH, 0.45A, 1.33 ohm, SMD	Vishay-Dale	IFSC0806AZER100M01			IFSC-0806AZ-01
15	3	Q1,Q2,Q5	2.6V	Transistor, NPN, 30V, 0.6A, SOT-23	ON Semiconductor	MMBT2222LT1G			SOT-23
16	1	Q3	0.075V	Transistor, PNP, 45V, 0.1A, SOT-23	Diodes Inc.	BC857C-7-F			SOT-23
17	1	Q4		NPN Transistor	Toshiba	2SC4738			SC-75-3
18	2	R12, R20	2.2Meg	RES, 2.2Meg ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW06032M20JNEA			0603
19	1	R5	2k	RES 2K OHM 1/4W 5% 0603 SMD	Rohm Semiconductor	ESR03EZP1202			0603
20	1	R7	300	RES, 300 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603300RJNEA			0603
21	1	R6	100	RES, 100 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603100RJNEA			0603
22	1	R8	6.8	RES, 6.8 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW06036R80JNEA			0603
23	1	R9	180k	RES, 180k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-07180KL			0603
24	1	R10	150k	RES, 150k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603150KJNEA			0603
25	1	R11	620	RES, 620 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603620RJNEA			0603
26	2	R3, R17	0	RES, 0 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW06030000Z0EA			0603
27	5	R16,R21,R23,R18,R19	10k	RES, 10k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW060310K0JNEA			0603
28	1	R13	3.9k	RES, 3.9k ohm, 5%, 0.1W, 0603	Yageo America	RC0603JR-073K9L			0603
29	1	R14	160k	RES, 160k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-07160KL			0603
30	2	R4,R15	47k	RES, 47k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW060347K0JNEA			0603
31	1	R24	270k	RES, 270k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603270KJNEA			0603
32	1	R1	510k	RES, 510k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603510KJNEA			0603
33	2	R2,R25	100k	RES, 100k ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603100KJNEA			0603
34	1	R26	100K	NTC Thermistors,0603 100k ohm +/-1%	Murata Electronics	NCP18WE104F12RB			0603
35	1	P1	4x1	230 mil above insulator	Samtec	TSW-104-07-G-5			TSW-104-07-G-5
36	1	P2		Buzzer	Murata	PKM24SPH3805			PKM24SPH3805
37	1	BT1		Battery Holder, CR123A, TH	Keystone	1051			Keystone_1051
38	3	U2,U3,U5		DUAL CHANNEL HIGH SPEED ESD PROTECTION DEVICE	Texas Instruments	TPD2E2U06DRL			DRL0005A_N
39	1	U4		28 V, 400 mA Switch Boost Converter for White LED Applications, 1.8 to 6 V, 40 to 85 degC, 5-pin SOT23 (DBV5), Green (RoHS & no Sb/Br)	Texas Instruments	TPS61040DBVR			DBV0005A_N
40	1	U1		MSP430FR2311 Mixed-Signal Microcontroller	Texas Instruments	MSP430FR2311			TSSOP16

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2019, Texas Instruments Incorporated